





TVS ESD and Surge Protection


- **High Surge Power TVS** (VBUS and VBAT, DCP Power Lines, etc.)
- **High Surge Current TVS** (Audio and CCx Lines in Type C, etc.)
- **ESD TVS** (USB, HDMI, Thunderbolt, etc.)



DFN1.0x0.6



DFN2.5x1.0



WLCSP0.6x0.3



TVS
ESD and
Surge
Protection

Product Specification Table

Part Number	V _{RWM} (V)	CH	Package	ESD (kV)		C _J (pF)	I _{PP} (A)	Major Application
				Contact	Air			
AOZ8S205BL2-05	5	2	WLCSP0.6x0.3-3	±9	±9	0.075	3	Antenna, RF Front End Module, Thunderbolt 4.0, PCIe, USB4
AOZ8S204BL2-05	5	2	WLCSP0.6x0.3-3	±20	±20	0.15	8.5	Antenna, RF Front End Module, Thunderbolt4.0, PCIe, USB4
AOZ8S207BLS-01	1	1	WLCSP0.6x0.3-2	±16	±16	0.15	5	Thunderbolt 4.0, USB4, PCIe
AOZ8S204BLS-05	5	1	WLCSP0.6x0.3-2	±20	±20	0.15	8.5	Thunderbolt 4.0, USB4, PCIe, HDMI2.1
AOZ8S205BLS-05	5	1	WLCSP0.6x0.3-2	±8	±8	0.075	3	Thunderbolt 4.0, USB4, PCIe, HDMI2.1
AOZ8S212UD4-05	5	4	DFN2.5x1.0-10L	±8	±10	0.2	3	HDMI 2.0, Display Port, USB3.0/3.1/3.2, V-by-One
AOZ8S204BLS-24	24	1	WLCSP0.6x0.3-2	±20	±20	0.2	8.5	Thunderbolt 4.0, USB4, PCIe, HDMI2.1
AOZ8S204BLS-30	30	1	WLCSP0.6x0.3-2	±20	±20	0.15	8.5	Thunderbolt 4.0, USB4, PCIe, HDMI2.1
AOZ8S305BLS-05	5	1	WLCSP0.6x0.3-2	±30	±30	0.5	20	USB3.x, USB2.0
AOZ8S305BLS-24	24	1	WLCSP0.6x0.3-2	±30	±30	0.5	20	Type-C USB3.0/3.1/2.0
AOZ8S306BD4-05	5.5	4	DFN2.0x1.0-10L	±11	±11	0.25	4	HDMI 2.0, Display Port, USB3.0/3.1/3.2, V-by-One
AOZ8S321UD4-05	5	1	DFN2.5x1.0-10L	±15	±15	0.28	5	HDMI 2.0, Display Port, USB3.0/3.1/3.2, V-by-One
AOZ8S325BDS-40	40	1	DFN1.0x0.6-2L	±8	±8	0.35	1	USB-PD3.1 CC-pin
AOZ8S507BDS-07	7	1	DFN1.0x0.6-2L	±30	±30	19	9	Power Rails Protection, General Purpose, Audio
AOZ8S515UDS-20	20	1	DFN1.6x1.0-2L	±30	±30	200	30	USB-PD3.0 VBus-pin
AOZ8S516UDS-28	28	1	DFN1.6x1.0-2L	±30	±30	150	25	USB-PD3.1 VBus-pin
AOZ8S530BLS-03	3.3	1	WLCSP0.6x0.3-2	±30	±30	30	35	Battery & VBUS Protection, General Purpose, Audio
AOZ8S530BLS-05	5	1	WLCSP0.6x0.3-2	±30	±30	15	28	
AOZ8S530BLS-07	7	1	WLCSP0.6x0.3-2	±30	±30	21	18	



AOS SALES OFFICES

UNITED STATES

475 Oakmead Pkwy
Sunnyvale, CA 94085
Phone: +1 (408) 830-9742
Email: Inquiries@aosmd.com

EUROPE

Phone: +49 7131 6446756
Email: AOSEurope@aosmd.com

JAPAN

5F, Yurakucho Building
1-10-1 Yurakucho
Chiyoda-ku
Tokyo 102-0083
Phone: +81 (3) 6826-1401
Email: AOSJapan@aosmd.com

SOUTH KOREA

10th Floor, Bandi Building
Bongeunsa-ro 114
Gangnam-gu
Seoul 135-907
Phone: +82 (2) 557-8501
Email: AOSKorea@aosmd.com

TAIWAN

9/F, No. 292 Yangguang Street
Neihu District
Taipei City 11491
Phone: +886 (2) 8751-5616
Email: AOSTaiwan@aosmd.com

HONG KONG

Room 701, Tesbury Center
28 Queen's Road East
Wanchai
Phone: +86 (755) 8351-7733
Email: AOSChina@aosmd.com

CHINA

SHENZHEN

East 8/F, Matsunichi Building
#9996 Shennan Blvd.
Shenzhen 518057
Phone: +86 (755) 8351-7733
Email: AOSChina@aosmd.com

SHANGHAI

Room 1002-1005, Tower 1
Kerry EverBright City
218 Tianmu West Road
Shanghai 200070
Phone: +86 (21) 6353-3218
Email: AOSChina@aosmd.com

To contact any of our sales partners worldwide, please visit our website at: www.aosmd.com/contact

Alpha and Omega Semiconductor Limited, or AOS, is a designer, developer and global supplier of a broad range of power semiconductor products. AOS's products are aimed at, but not limited to applications such as portable computers, flat panel TVs, LED lighting, smart phones, battery backs, consumer and industrial motor controls, automotive electronics, and power supplies for TVs, computers, servers and telecommunication equipment.



Powering a Greener Future™